آموزش نصب و راه اندازی فیش پرینتر حرارتی

1. در ابتدا باید نرم افزار مخصوص فیش پرینتر که معمولا به صورت سی دی در جعبه دستگاه موجود می باشد نصب شود. (در صورت نداشتن سی دی نرم افزار، می توانید از سایت aradsoftware.com قسمت دانلود،درایور مورد نظر را دانلود و مراحل نصب را شروع کنید.)

2. از فولدر نصب فولدر driver را باز کنید و سپس فولدر windows driverرا باز کنید و فایل pos printer driver setup را اجرا کنید .

3.گزینه l accept the agreement را انتخاب کنید و دکمه Next را بزنید.

		-
License Agreement		FY
Please read the following import	ant information before continuing.	(10)
Please read the following Licens agreement before continuing wi	e Agreement. You must accept the terms of this th the installation.	
SOFTWARE LICENSE AGREEME	NT	^
IMPORTANT - PLEASE READ CA	AREFULLY! The POS software you are about to	
download will be licensed to you	u, the licensee, on the condition that you agree	
READ THIS AGREEMENT CAREF	FULLY. YOU WILL BE BOUND BY THE TERMS OF	
THIS AGREEMENT IF YOU INST	ALL, DOWNLOAD, COPY, OR OTHERWISE USE	
please do not install or downloa	ad the software. Please record the date of	
download in order to activate t	he limited ninety (90) day warranty (see below).	~
I accept the agreement		

4.بر روی next کلیک کنید،سپس yes را بزنید.

up		×
Select Destination Location		EPP
Where should POS Printer Driver V7.17 be	installed?	(10m)
Sotup will install POS Printer Drive	or V7 17 into the following fo	lder
Setup will install POS Printer Drive	er v7.17 into the following fo	waer.
To continue, click Next. If you would like t	o select a different folder, cl	ick Browse.
C:\POS Printer Driver V7.17		Browse
At least 13.1 MB of free disk space is requ	iired.	
At least 13.1 MB of free disk space is requ	iired.	

5. next را بزنید.

etup		×
Select Additional Tasks		FR
Which additional tasks should be pe	rformed?	(10)
Select the additional tasks you wou Driver V7.17, then dick Next.	ld like Setup to perform while installing P	OS Printer
Additional shortcuts:		
Create a desktop shortcut		
		86
	Back Next	Cancel
	. تا مراحل نصب شروع شود	کمه install را فشار را دهید
·		

2000 C		×
Ready to Install	rin installing DOC Brinter Driver V7-17 on vour	E
computer.	jin installing POS Printer Driver V7.17 on your	
Click Install to continue w change any settings.	th the installation, or click Back if you want to review	or
Destination location: C:\POS Printer Drive Additional tasks: Additional shortcuts: Create a desktop :	r V7.17 ;hortcut	^
<		> ~
	Back Install	Cancel
Setup	ک کنید.	7.بعداز نصب برروی finish کلیــــــــــــــــــــــــــــــــــــ
	Completing the POS Printer	Driver
	V/II/ SCLUP WIZUIU	
EN	Setup has finished installing POS Printer Driver V7. computer. The application may be launched by sele installed shortcuts. Click Finish to exit Setup.	17 on your ecting the
HON	Setup has finished installing POS Printer Driver V7. computer. The application may be launched by sele installed shortcuts. Click Finish to exit Setup. Launch POS Printer Driver V7.17	17 on your acting the
	Setup has finished installing POS Printer Driver V7. computer. The application may be launched by sele installed shortcuts. Click Finish to exit Setup. Launch POS Printer Driver V7.17 Finish	17 on your acting the

8.در پنجره بازشده نوع ویندوز،نوع اتصال پرینتر و مدل پرینتر(pos-80c) را انتخاب کنید و دکمه install now

را انتخاب کنید.

rou are using windows 10 Please select Windows 10) x64 OS. to install.
Select Windows OS	
C Windows XP	C Windows Vista
C Windows 2003	C Windows 8/8.1
C Windows 7	Windows 10
C Windows 11	
Select Printer Series	C POS-58C
POS-80C	C POS-90
C POS-76	C POS-76C
*Remarks: "C" means ite	m with cutter

9.در پنجره بازشده پورت مورد نظر را انتخاب کنید و okرا بزنید.

	Juding	, one	Auvanceu	Color Management	Jecunty	Device Jetti	iya
5	POS	-80C					
Print to checke	o the foll ed port.	owing p	ort(s). Docu	ments will print to	the first fr	ee	
Port		Descript	ion	Printer			•
	OM4:	Serial Po	ort				
🗌 FI	LE:	Print to	File				
	SB001	PrinterP	OS-80				
	SB002	Unknow	nPrinter				
	SB003	Virtual p	rinter port f	or 4BARCODE 4	B-2054TA		
	92.16	Standard	d TCP/IP Por	t			
	ORIP	Local Po	ort	Microsoft XP	SDocume	ent Write	1
	Add Por	t	D	elete Port	Confi	gure Port	
Ena	ble bidir	actional	cupport				
			support				
Ellg	ine huur	er poolii	19				
0							

8.حال به قسمت devices and printer سیستم بروید. بر روی فیش پرینتر نصب شده کلیک راست و گزینه printer properties را بزنید..

+ → * ↑	🛱 > Control Panel	> All Control Panel	Items > Devices and P	rinters >					~ Ö	Search De	evices and	- 5
Add a device	Add a printer S	ee what's printing	Print server propertie	s Remove device							•	
19M35	DESKTOP-ARADS OF	Pioneer external optica持期间资 單V	usb keyboard	USB OPTICAL MOUSE								
Vultimedia [Devices (3)											
)											
Arad (arad-pc)	DESKTOP-VKN22	HWI-PC										
rinters (8)	QA							-				
	Se la compañía de la	·					8	1				
4BARCODE	Fax	HP Color LaserJet	Microsoft Print	Microsoft XPS	OneNote for	pdfFactory Pro	POS-80C	See what's printing				
48-2054TA		Pro M252 PCL 6	to PDF	Document Writer	Windows 10			Set as default printer				
Unspecified ((1)							Printing preferences Printer properties				
								Create shortcut				
								S Remove device Troubleshoot				

9. دکمه test page در قسمت پایین سمت راست را فشار دهید. درصورت چاپ گرفتن تست ویندوز شما توانسته اید به طور صحیح درایور را نصب و راه اندازی کنید.

General	Sharing	Ports	Advanced	Color Management	Security	Device Settings
\$	[POS-80	C			
Locati	on:					
Comm	nent:					
Model	:	POS-80	c			
Feat Cole	ures or: No			Paper availabl	e:	
Dou Stap Spe	ible-sideo ole: No ed: Unkn	d: No own		80(72.1) x 29	7 mm	^
Max	cimum re	solutior	n: 203 dpi			~ .
			De	oforon.cor	Print	Test Page